


*根据输出功率选取外置MOS管，M和M1 M2只选一种方案即可

输出电压计算：V1V2 V3全关时：VOUT=1.2V*(R1+R2)/R3+1)
 仅V1开时：VOUT=1.2V*(R1+R2)/(R3[R4]+1)
 仅V1 V2开时：VOUT=1.2V*(R1+R2)/(R3[R4]R5)+1)
 V1 V2 V3全开时：VOUT=1.2V*(R1+R2)/(R3[R4]R5[R6]+1)

编号	D+	D-	V1	V2	V3	输出电压
1	0.6V	GND	OFF	OFF	OFF	默认5V
2	3.3V	0.6V	ON	OFF	OFF	9V
3	0.6V	0.6V	ON	ON	OFF	12V
4	3.3V	3.3V	ON	ON	ON	20V

*备注：V1/V2/V3脚的ON表示把此脚拉到地，OFF表示此脚悬空
 *U2与U2-1 同型号不同封装，任贴一颗



Title		
Size	Number	Revision
A4		
Date:	19-Jul-2016	Sheet of
File:	E:\张春峰\做DEMO\DEMO.ddb	Drawn By: